


Update TDA/TVM/TE USB Driver under Windows XP


1. When you plug-in a device to your PC, there will be a plug-in device icon (the green arrow icon) at the right bottom corner (system tray).



2. After double-click this icon, the follow plug-in device list will appear.




3. After selecting the device, click “Properties” to open the device properties dialog.
* Don’t double-click the device on the above screen. Windows takes the double-click operation as “Stop” by default.




4. On the above screen, click “Update Driver” to start update process. On the following screen, select “No, not this time” so that we can specify the driver file directory ourselves.




5. Then the following screen will appear.




6. On the above screen, select “Advanced” to install the driver. On the following screen, select “Don’t search. I will choose the driver to install.”



7. Then the following screen will appear.




8. Select "Have Disk".




9. On the above screen, browse to the driver file directory, and then click “OK”. The following Windows XP warning dialog will appear.




10. We can ignore the warning. It is because our driver hasn't passed Windows LOGO test. Click “Continue Anyway”. After the driver files are copied, the driver update will be finished.



11. The device properties dialog will be updated to the latest driver version.



12. If you update the driver while running some TDA/TVM/TE applications, especially when the TSP system service is running at the background, Windows will ask you to reboot the PC. Click "OK" to reboot the PC.



13. After PC is rebooted, the driver will be updated to the latest version.